SKE Bharat | Specification sheet

Microtek Luxe WiFi

Home Inverters & UPS | SKU SKE-MTK-002

Pure sine wave inverter with WiFi connectivity for monitoring; listed as the 1400 (12 V, 1100 VA) inverter and as bundles with tubular batteries. Also searched as: Microtek Luxe WiFi inverter, Microtek Luxe 1400 WiFi, Microtek WiFi inverter, Microtek inverter with mobile app, Microtek Luxe WiFi inverter battery combo

Specification

Brand	Microtek
Product Type	Home Inverters & UPS

Typical applications

- Homes
- Offices
- Shops

Key features

- 1100VA / 825W pure sine wave inverter - ensures stable and noiseless power for sensitive appliances.
- Provides up to 1.35 hours backup on a 350W load including mixer grinder, kitchen chimney, fan, light, TV, router, laptop, and mobile charging.
- Smart WiFi connectivity - monitor inverter performance, battery status, and backup time via the Microtek mobile app.
- Wide input voltage support - Inverter Mode: 80V-290V | UPS Mode: 180V-265V.
- Universal battery compatibility - supports Tubular, SMF, FLA, and Lithium batteries.
- Multiple charging currents - selectable 10A / 12A / 15A / 20A for efficient and safe battery charging.
- Advanced protections - safeguards against overload, short-circuit, overcharge, overheating, back-feed, and high DC voltage.

Models and ratings

Model	Rating (from product	Output voltage (as li	Weight (as listed)	Dimensions (as listed
LUXE WIFI 1400 12V Pu	1100 VA	230 Voltage	10.3 KG	33.5*18.3*33

To get a quotation, send us

- Model or the load / capacity you need
- Quantity and delivery location
- Installation details (home, office, plant, solar, telecom)
- Any specific requirement, such as battery type or backup time

Request a quotation

skebharat.com/product/microtek-luxe-wifi/

+91 88844 93900 | yeswanth@skebharat.com | Rajaji Nagar, Bangalore

SKE Bharat (SBYKSF Private Limited)

Summarised from the product page at skebharat.com. Ratings, standards and dimensions are confirmed in your quotation.